

DS7400Xi Series Addressable Control Panels

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Up to 248 zones in up to eight areas
- ▶ 400-event history buffer
- ▶ Up to 200 personal ID numbers (PINs)
- ▶ Up to 112 wireless devices
- ▶ Up to 15 keypads and/or door access control modules (DACMs)

The DS7400Xi Series Addressable Control Panels can be programmed for up to eight areas, are keypad or remotely programmable, and have a wide range of features.

Functions

Answering Machine Override

Each control panel model has a built-in answering machine override function. No external hardware is required.

Automatic Arming and Delayed Arming

Program an automatic arming time for each area daily. Use delayed arming to override automatic arm time or to specify a time for the panel to arm.

Common Area Arming

Program one area to follow the arming state of some or all of the other areas. The common area arms only when all areas linked to it are armed, protecting shared areas such as foyers and entry-ways while maintaining separate areas.

Custom Arming Configurations

Program the system to arm in different configurations to automatically bypass a group of zones.

Easy Function Key User Interface

- Six labeled function keys eliminate the need for multi-button commands. Enter a PIN followed by the function key to perform functions such as arming, disarming, and resetting smoke detectors.
- The interface provides new users with easy to follow procedures. Expert users can quickly access items.
- A programmable Quick Arm feature allows users to turn the system on without a PIN. The system requires a PIN to turn off the system, silence alarms, or perform system tests.

EEPROM Technology

The control panel uses electronically erasable programmable read-only memory (EEPROM). The EEPROM retains program memory, system programming, user codes, and the arm/disarm state through a power failure. There is a delay on power restore that prevents false alarms from space sensors that might take several minutes to become operational.

Eight Areas

Divide the control panel into eight separate system areas, each area with its own keypads and reporting ID. Keypads can be programmed as master keypads, allowing access to all areas.

Flexible Digital Communication

The communicator works with most alarm receivers, and supports 3/1, 4/1, 4/2, Contact ID, SIA, BFSK digital communicator formats and pager format. The pager format allows the control to dial a digital pager service and leave a numeric message representing the account number and event code.

Input and Output Cross Matrix

Input and output cross matrix allows output functions to follow the status of specific input zones. Outputs can be programmed to follow any combination of one or two zones, open or closed, with the system armed or disarmed.

LED and Alphanumeric Keypad Support

- **DS7445V2 LED Keypad:** Provides an LED per zone (LEDs 1-8 for main board zones and LEDs 9-16 for expansion zones), and eight system status LEDs that show conditions such as armed, fire alarm, and trouble.
- **DS7445i LED Keypad:** Provides an LED per zone (for main board zones 1-8 only), and eight system status LEDs that show conditions such as armed, fire alarm, and trouble.
- **DS7447V2 Alphanumeric Keypad:** Two line, freely programmable display allows 16 characters of custom text to be programmed for zone and area descriptions. The user can adjust the sounder volume and backlight intensity using easy two-button commands. The DS7447V2 is required for system programming.

Note: LED and LCD keypads may be mixed in the same system.

Octal Relay Modules

The DS7400Xi Series Control Panels support up to two DX3010 Octo-Output Expander Modules. Each module supplies eight relay or solid state outputs to follow system events or to follow programmed Output Functions from the control panel.

Output Functions

Program the output functions to follow system events or to follow one or two specific zones in a cross matrix (see Input and Output Cross Matrix). Output functions can control octal relay outputs or addressable bus outputs.

Programmable from Keypad or Remotely

- The system is completely keypad programmable. No need for expensive handheld programmers.
- RPS-INTL provides remotely programming through an IBM PC (or IBM compatible) running a Microsoft Windows operating system and communicating through a standard Hayes modem. Using an off-site

computer to run diagnostics, arm systems, and bypass zones reduces service visits to a premise and provides quick customer assistance.

Smoke Detector Alarm Verification

The DS7400Xi Series Control Panels can automatically reset the smoke detectors following an alarm. If a second alarm occurs within the verification window, an immediate fire alarm occurs, reducing potential false alarms while providing fast response to an alarm.

Two Independent Entry Delays

Program zones to select from one of the two entry delay times. Users can select a longer entry delay time for zones located a long distance from the keypad.

Certifications and approvals

Region	Certification	
Europe	CE	2004/108/EC EMC Directive (EMC); 2006/95/EC Low-Voltage Directive (LVD) [DS7400XU16 panel family]
	CE	2004/108/EC EMC Directive (EMC); 2006/95/EC Low-Voltage Directive (LVD); 2011/65/EU Restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS) [PCB board only]
Belgium	INCERT	B-509-0003/c (DS7400Xi16-SWE only)
China	CCC	DS7400Xi-CHI: 2009031902000556
Sweden	INTYG	04-755

Installation/configuration notes

Compatible Products

Category	Product
Keypads	DS7445Vi LED Keypad
	DS7445V2 LED Keypad
	DS7447E LCD Keypad
	DS7447V2 LCD Keypad
Modules	Conetix IP C900V2 Dialer Capture Module
	C900TTL-E Dialer Capture Module
	Conetix IP DX4020 Network Interface Module
	Door Access Control Module (DACM)
	DS7420i Dual Phone Line/Bell Supervision Module
	DS7430 Multiplex Bus Driver Module
	DS7432/E Eight-Input Remote Module
	DS7433/E Eight-Input Direct Module
	DS7436 Addressable Expansion Module
	DS7457i/iF Single-Zone Input Module
DS7457iE Single-Zone Input Module	

	DS7460i Double-Input Module
	DS7461i Single-Input Module
	DS7465i Input/Output Module
	DS7480 Bell Supervision Module
	DS7481 Single Phone Line Monitor
	DS7489 Solid State Output Module
	DX3010 Octo-output Expander
	DX4010i RS-232 Serial Interface Module
Multiplex Detectors	D7050/TH Multiplex Photoelectric Smoke Detector
	MX250/TH Multiplex Photoelectric Smoke Detector
	MX775i Multiplex PIR Intrusion Detector
	MX794i Long-Range Multiplex PIR Detector
	MX934i Multiplex PIR Intrusion Detector
	MX938i Multiplex Intrusion Ceiling Mount Detector
Intrusion Detectors	All conventional Bosch intrusion detectors, including Blue Line, seismic, PIR, TriTech, photoelectric, and TriTech PIR Microwave.
Two-wire and Four-wire Smoke Detectors ¹	Conventional Bosch 12 V smoke, heat, and photoelectric smoke detectors.

¹ Availability varies according to sales regions.

Wiring

Use four-conductor 1.2 mm to 0.8 mm (18 AWG to 22 AWG) cable. The maximum wire length of each sensor loop is 305 m (1000 ft). The maximum multiplex bus wire length per system is 610 m (2000 ft) if using 0.8 mm (22 AWG) wire or 1525 m (5000 ft) if using 1.0 mm (18 AWG) wire.

Keypads

No more than two keypads per 305 m (1000 ft) run with a total of no more than 15 keypads in the system.

Technical specifications

Burglar and Fire Zone Inputs

Number of Circuits:	8 circuits on board
End of Line Resistor:	2.2 + 1.5 k Ω

Environmental Considerations

Operating Temperature:	0°C to +49°C (+32°F to +120°F)
------------------------	-----------------------------------

Fire Signal Initiating Circuit

Fire circuits will work with two-wire or four-wire detectors and have optional alarm verification.

Number of Circuits:	8 circuits on board, expandable to 16
Type of Circuit:	Class B, latching
End of Line Resistor:	2.21 k Ω
Supervisory Current:	5 mA
Minimum Current for Alarm:	12 mA
Maximum Short Circuit Current:	22 mA
Maximum Circuit Resistance:	60 Ω
Circuit Voltage Range:	8.5 VDC to 14.1 VDC
Maximum Impedance for Alarm:	1000 Ω
Maximum Detectors per Zone:	20 detectors (two-wire)
Total Detector Standby Current:	2.5 mA

Lightning Suppression

MOVs and spark gaps provide suppression of lightning surges and static discharges.

Outputs

The system provides three programmable outputs that can be controlled by alarms, access control, ground start, smoke detector reset, or the control's arming state.

Alarm Output:	Normally Open, 1.75 A contact connected to auxiliary power.
Programmable Output 1:	Solid state current sink (1 A maximum). Can be used for alarm, arming state, or access control.
Programmable Output 2:	Solid state voltage source (500 mA maximum). Can be used for alarm, arming state, or access control.

Power Requirements

Input:	18 VAC, 50 VA, 50 Hz or 60 Hz
Total Power Output:	12 VDC, 2.5 A
Keypad Regulated Power:	12 VDC, 1.0 A
UL Listed Auxiliary Power:	12 VDC, 1.0 A
UL Listed Alarm Power Output:	1.75 A

Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses

the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

IBM is a registered trademark of IBM in the United States.

Microsoft and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and other countries.

Ordering information

DS7400XI-EXP Control Panel

For export. Includes a transformer and enclosure.
Order number **DS7400XI-EXP**

DS7400XI-BEL Control Panel

For use in Belgium. Includes a large enclosure. Always has 128 points enabled.
Order number **DS7400XI-BEL**

DS7400XI-CHI Control Panel

For use in China. Includes an enclosure.
Order number **DS7400XI-CHI**

DS7400XI-DK Control Panel

For use in Denmark.
Order number **DS7400XI-DK**

DS7400XI-GR Control Panel

For use in Greece. Includes an enclosure.
Order number **DS7400XI-GR**

DS7400XI-FI Control Panel

For use in Finland.
Order number **DS7400XI-FI**

DS7400XI-FRA Control Panel

For use in France.
Order number **DS7400XI-FRA**

DS7400XI-HU Control Panel

For use in Hungary. Includes an enclosure.
Order number **DS7400XI-HU**

DS7400XI-ITA Control Panel

For use in Italy.
Order number **DS7400XI-ITA**

DS7400XI-NOR Control Panel

For use in Norway. Includes an enclosure.
Order number **DS7400XI-NOR**

DS7400XI-SPA Control Panel

For use in Spain.
Order number **DS7400XI-SPA**

DS7400XI-SWE Control Panel

For use in Sweden. Includes an enclosure.
Order number **DS7400XI-SWE**

DS7400XI16-BEL Control Panel

Provides 16 zones. For use in Belgium.
Order number **DS7400XI16-BEL**

DS7400XI16-SWE Control Panel

Provides 16 zones. For use in Sweden.
Order number **DS7400XI16-SWE**

DS7400Xi Control Panel for the US

Order number **DS7400Xi**

Accessories

AE1 Standard Enclosure (Gray)

Standard gray enclosure with keyed lock. Measures 35.6 cm x 31.8 cm x 7.6 cm (14 in x 12.5 in x 3 in).
Order number **AE1**

AE3 Large Enclosure (Gray)

Large gray enclosure with keyed lock. Measures 52.7 cm x 38.1 cm x 10.8 cm (20.7 in. x 15 in. x 4.25 in.).
Order number **AE3**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com