



RF3212 Series RF Receivers



- ▶ **Receives low battery, tamper, and sensor status reports**
- ▶ **LED indicates receiver status**
- ▶ **Cover tamper with optional wall tamper**
- ▶ **Diversity antennas**

The RF3212 Series RF Receivers include the following models:

Model	RF Transmission
RF3212	304.00 MHz
RF3212E	433.42 MHz

Each model allows Bosch I/P bus control panels to receive RF signals from wireless devices. The wireless devices save time for busy installers and homeowners and the receivers are a valuable option for system users who want additional security without disruptive installations. Tamper, jam detection, and sensor missing status reports confirm that the system is working properly.

- Do not mount the receiver in areas with significant metal or electrical wiring such as furnace rooms and utility rooms. If this is unavoidable, mount the receiver with the antennas extending above any metal surface.
- Avoid exposing the receiver to moisture.
- Reception distances improve with higher mounting locations and without metal objects near the receiver antennas.
- Building materials can reduce the overall range.

Compatibility Information

Receiver	Control Panels
RF3212 and RF3212E	Solution Ultima CC488

Certifications and Approvals

Model	Certifications and Approvals
RF3212E	CE

Installation/Configuration Notes

Mounting Considerations

- Mount the receiver in a central location in respect to all wireless sensors.
- Mount the receiver on a vertical surface with at least 25 cm (10in.) clearance for the antennas.

Technical Specifications

Environmental Considerations

Temperature (Operating): -20°C to +65°C (-4°F to +150°F)

Mechanical Properties

Dimensions: 10.8 cm x 15.2 cm x 3.1 cm
(0.25 in. x 6 in. x 1.2 in.)

Power Requirements

Current Draw: 30 mA nominal

Voltage (Input): 12 VDC

Reception Characteristics

RF3212

Frequency: 304.00 MHz

Range (open air): 91 m (300 ft) nominal Up to 274 m (900 ft) if jam is off

RF3212E

Frequency: 433.42 MHz

Range (open air): 305 m (1000 ft)

Ordering Information

RF3212 RF Receiver (304.00 MHz)	RF3212
RF3212E RF Receiver (433.42 MHz)	RF3212E

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by