

# B10R-1640-120WI Medium Control Panel Enclosure

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Enclosed 16.5 VAC 40 VA transformer
- ▶ Easy to install standoff locations for mounting supporting modules
- ▶ Red matte finish for fire applications
- ▶ Punch outs for optional B46 External Annunciator (for B465 only)
- ▶ Additional slow-blow fuse included in fuse block

The B10R-1640-120WI Red Medium Enclosure with 16.5 VAC 40 VA Transformer houses the D1640-120WI wired-in transformer, and select Bosch control panels and modules. The enclosure is compatible with an optional enclosure tamper switch and optional lock and key set, and holds one 7 or 18 Ah batteries.

## Installation/configuration notes

### Compatibility

Devices	B465 Conettix Universal Dual Path Communicator B46 External Annunciator D101 Lock and Key Set ICP-EZTS Tamper Switch Set D110 Tamper Switch
---------	---

## Parts included

Quantity	Component
1	B10R-1640-120WI enclosure

1	Hardware pack
1	Installation Guide (hardcopy)

## Technical specifications

### Properties

Dimensions	14 in x 12.5 in x 3 in (35.6 cm x 31.8 Cm x 7.6 cm)
Material	1.0 mm (20 gauge) cold-rolled steel
Color	Red

### Environmental considerations

Temperature (operating)	0°C to +49°C (+32°F to +120°F)
Mounting considerations	Mount in dry indoor locations.

### Power requirements

Voltage (operating)	120 VAC nominal to fuse block
Current (maximum)	< 0.5 A

Fuse	0.5 A slow 250 V 5x20 mm
Terminal wire size	2 mm to 0.65 mm (12 AWG to 22 AWG)

### Ordering information

#### **B10R-1640-120WI Medium Control Panel Enclosure**

Red, steel enclosure with an attached with 16.5 VAC 40 VA transformer. Accepts an optional lock and tamper switch.

Order number **B10R-1640-120WI**

#### **Accessories**

##### **D101 Lock and Key Set**

Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Order number **D101**

##### **ICP-EZTS Dual Tamper Switch**

Combination tamper switch with a wire loop for additional tamper outputs.

Order number **ICP-EZTS**

##### **D110 Tamper Switch**

Screw-on tamper switch that fits all enclosures.

Shipped in packages of two.

Order number **D110**

#### Represented by:

##### **North America:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### **Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### **Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### **China:**

Bosch (Shanghai) Security Systems Ltd.  
203 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### **Latin America and Caribbean:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com