

B926F Teclado de incêndio, SDI2

www.boschsecurity.com.br



BOSCH
Tecnologia para a vida



- ▶ Teclado de incêndio com teclas de função de incêndio: ACK, SILENCE, RESET e DRILL
- ▶ display LCD de 2 linhas com nomes de ponto, usuário e área até 32 caracteres
- ▶ Interface de usuário do estilo menu com botões de função dedicados para comandos comuns, incluindo indicação de estado
- ▶ Indicadores visuais para estados críticos do sistema identificáveis rapidamente
- ▶ Instalação simples com desenho da base e do chassis de auto-bloqueio e nível de bolha de ar incorporado

The B926F Fire Keypad is a fully supervised SDI2 device for fire applications.

Each keypad has user-adjustable backlit keys, a display that shows system messages, and a sounder. The sounder emits distinct condition tones to alert you to a fire alarm, a fire trouble, or fire supervisory events as they occur. The keypad includes fire status indicators and fire function keys.

Funções

LCD display

O teclado utiliza palavras, números e símbolos para mostrar o status do sistema de segurança. Quando vários eventos ocorrem, o teclado mostra cada um em ordem de prioridade.

Keys

Each keypad has 10 number keys and 5 navigation keys.

When pressed, keys turn on keypad backlighting and emit the keypress tone (short beep). The keypad has 4 Fire function keys:

- ACK. Press to acknowledge the system alarm or trouble condition.
- SILENCE. Press to silence fire alarms or troubles.

- RESET. Press to reset devices such as smoke detectors, and clear restored points.
- DRILL. Press and hold to initiate a fire drill.

Audible tones

The keypad has a built-in sounder that produces several distinct warning tones. The tones are differentiated so that the user can recognize an event simply by hearing its associated tone.

Status indicators

The status indicators on the keypad provide a quick visual reference for system status.

	The indicator lights when the system is ready to turn on (arm).
	The indicator lights when the system is on (armed).
	The indicator lights when dangerous gases are present including carbon monoxide (NFPA 720).
	The indicator lights when the system has power.

Fire status indicators

In conjunction with the display and status indicators, the fire keypad includes Fire status indicators.



The indicator lights when a fire alarm condition exists.



The indicator lights when a user silenced a fire alarm condition.



The indicator lights when a supervisory point is not normal.



The indicator lights when there is a trouble condition

Certificados e aprovações

Região	Conformidade normativa/marcas de qualidade	
EUA	ANSI-SIA	CP-01-2010-Control Panel Standard - Features for False Alarm Reduction
	UL	UL 365 - Police Station Connected Burglar Alarm Units
	UL	UL 609 - Standard for Local Burglar Alarm Units and Systems
	UL	UL 636 - Holdup Alarm Units and Systems
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems
	UL	UL 985 - Household Fire Warning System Units
	UL	UL 1023 - Household Burglar Alarm System Units
	UL	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL	UL 1610 - Central Station Burglar Alarm Units
	UL	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	UL	UL 294 - Standard for Access Control Units and Systems
	UL	UL 1635 - Standard for Digital Alarm Communicator System Units
	CSFM	California Office of The State Fire Marshall
Canadá	ULC	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	ULC	CAN/ULC S304 - Standard for Signal Receiving Center and Premise Burglar Alarm
	ULC	CAN/ULC S545 - Residential Fire Warning System Control Units
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems

Região	Conformidade normativa/marcas de qualidade	
	ULC	[B9512G, B9512G-E, B8512G, B8512G-E, B299, B600, B901, B925F, B926F]
	IC	ICES-003 - Information Technology Equipment (ITE)

Notas de instalação/configuração**Considerações de montagem**

Montagem em ambientes internos e secos.

Fonte de alimentação

Um painel de controle compatível fornece os requisitos de alimentação e dados para o teclado através de uma conexão de quatro fios.

Gabinete e fiação

O gabinete deslizante e autotravante tem um nível de bolha integrado e blocos de terminais com modelo personalizado de porta de elevação sem fenda para facilitar a instalação.

Compatible control panels

B9512G/B9512G-E

B8512G/B8512G-E

Peças incluídas

Quantidade	Componente
1	Teclado
1	Pacote de hardware
1	Manual de instalação
1	Guia de consulta rápida do usuário

Especificações técnicas**Requisitos de alimentação elétrica**

Corrente	Em espera: 35 mA Alarme: 70 mA
Tensão (entrada)	12 VCC nominal

Materiais e recursos de hardware

Dimensões	158 mm x 120 mm x 26 mm (6.2 in x 4.7 in x 1 in)
Peso	0,32 kg (11,3 oz)
Material	Acrilonitrila butadieno estireno (ABS) Poli(metacrilato de metila) (PMMA)
Janela do visor	Visor com duas linhas 18 caracteres por linha
Indicadores	Teclas iluminadas Indicadores de status Avisos e tons indicadores

Fiação

Tamanho do fio do terminal	De 1.02 mm (18 AWG) a 0.65 mm (22 AWG)
Fiação SDI2	Distância máxima - tamanho do fio: 260 m (850 pés) – 0.65 mm (22 AWG) 305 m (1000 ft) - 1.02 mm (18 AWG)

Considerações ambientais

Umidade relativa	5% a 93% a +32°C (+90°F)
Temperatura (de operação)	0°C a +49°C (+32°F a +120°F)

Informações sobre pedidos

B926F Teclado de incêndio, SDI2

Two-line alphanumeric fire keypad

Número do pedido **B926F**

Acessórios

B56 Caixa de instalação para teclado

Caixa para montagem de teclado em superfície de concreto ou bloco.

Número do pedido **B56**

B96 Placa decorativa para teclado

Cubra as marcas na parede dos teclados anteriores ao substituí-los pelos novos teclados Série B de design fino. A moldura de acabamento branca mede 22 mm x 16 mm x 3 mm (8,6 pol. x 6,3 pol. x 0,12 pol.).

Número do pedido **B96**

Representado por:

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Latin America and Caribbean:
Robert Bosch Ltda
Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
LatAm.boschsecurity@bosch.com
la.boschsecurity.com